
CW and RTTY Skimmer and the Reverse Beacon Network

Presented by N6TV n6tv@arrl.net








Overview



- What is CW Skimmer and RTTY Skimmer?
- What is the Reverse Beacon Network?
- How does it work?
- What can the RBN do for me?
- How can I use it?
- How can I help?
- What's new?




It all starts with one developer



Alex Shovkoplyas, VE3NEA

 (b. 1965, ex-UR5EMI, in Canada since 1998)






Honored as RAC Radio Amateur of the Year for 2014





What is CW Skimmer?



 Hardware: PC + Software Defined Radio (SDR)











SDR Antenna



2. Wideband RX Antenna, 1.8-30 MHz, e.g. DX Engineering (formerly Pixel) Magnetic Loop RF-PRO-1B® or ARAH3-1P Active

Dipole:









Software



3. CW (or RTTY) Skimmer or Skimmer Server










CW Skimmer by VE3NEA







- Works with many SDRs
- Decodes multiple CW signals in real time
- Can monitor entire CW band
- Waterfall Display
- Band Scope
- Uses MASTER.DTA
- Telnet Server (emulates a DX Cluster)





Skimmer Server by VE3NEA







- Natively supports only the QS1R SDR
- Decodes multiple CW signals in real time
- Monitors multiple bands with single SDR
- No Waterfall Display
- No Band Scope
- No MASTER.DTA
- Telnet Server



RTTY Skimmer Server (new)








- Natively supports only the QS1R SDR
- Decodes multiple RTTY signals in real time
- Monitors multiple bands with single SDR
- Limited Band Scope
- Can use MASTER.DTA
- Telnet Server





Telnet server (localhost port 7300)



Emulates a DX Cluster Node

```
DX de N6TU-#:
                  14058.7
                            WR7HE
                                            24 dB
                                                    31 WPM
                                                                            2350
                                                             CQ
                                                    25 WPM
                                                                            2350
DX de N6TU-#:
                  14029.6
                            NM7D
                                            29 dB
                                                             CQ
                  14059.5
                                            35 dB
                                                    31 WPM
                                                                            2350
DX de N6TU-#:
                            YW4D
                                                             CQ
DX de N6TU-#:
                  14022.6
                            J39BS
                                            11 dB
                                                    25 WPM
                                                             CQ
                                                                            2350
                                                                            2350
DX de N6TU-#:
                  14066.8
                            NF6A
                                            38 dB
                                                    30 WPM
                                                             CQ
DX de N6TU-#:
                            N5UM
                                            26 dB
                                                    28 WPM
                                                             CQ
                                                                            2350
                  14054.4
                  14021.2
                                            35 dB
                                                    31 WPM
                                                                            2350
  de N6TU-#:
                            NN5J
                                                             CQ
                  14061.4
                            WX58
                                            12 dB
                                                    28 WPM
                                                             CQ
                                                                            2350
DX de N6TU-#:
DX de N6TU-#:
                  14064.2
                            WQ5L
                                            15 dB
                                                    28 WPM
                                                                            2350
DX de N6TU-#:
                  14032.2
                            UE7XF
                                            18 dB
                                                    27 WPM
                                                                            2350
                  14042.9
                            NT5C
                                                    31 WPM
                                                                            2350
DX de N6TU-#:
                                            45 dB
                                                    27 WPM
DX de N6TU-#:
                  14032.2
                            UE7XF
                                            18 dB
                                                             CQ
                                                                            2350
                  14039.2
                            EA3FP
                                            15 dB
                                                    31 WPM
                                                                            2350
DX de N6TU-#:
DX de N6TU-#:
                  14052.5
                            WØYR
                                            20 dB
                                                    28 WPM
                                                             CQ
                                                                            2350
                  14022.9
                            AB7E
                                            32 dB
                                                    25 WPM
                                                                            2350
DX de N6TU-#:
DX de N6TU-#:
                  14028.4
                            WH6R
                                             7 dB
                                                    29 WPM
                                                                            2350
                  14065.6
                                            25 dB
                                                    29 WPM
                                                                            2350
DX de N6TU-#:
                            KH7B
To ALL de SKIMMER <0952Z> : Clicked on "UE7XF"
                                                   at 14032.2
DX de N6TU-#:
                  14069.6
                            KF6T
                                            13 dB
                                                    28 WPM
                                                                            2350
                  14069.1
                                            25 dB
                                                                            2350
DX de N6TU-#:
                            NKØM
                                                    28 WPM
To ALL de SKIMMER <0952Z> : Clicked on
                                          "" at 14031.4
                  14035.5
                                                    26 WPM
DX de N6TU-#:
                            KF8GE
                                            12 dB
                                                                            2350
DX de N6TU-#:
                                                                            2350
                  14028.4
                                              7 dB
                                                    29 WPM
                            WH6R
                                                             CQ
                            NZ1U
                                            16 dB
                                                    28 WPM
                                                                            2350
DX de N6TU-#:
                  14036.1
                                                             CQ
                                                                            2350
DX de N6TU-#:
                  14062.7
                            N4QS
                                            11 dB
                                                    29 WPM
                                                             CQ
                                             20 AB
                                                    22 LIDM
                                                                            2350
DX de N6TU-#:
                  14045.1
                            YU1FM
DX de N6TU-#:
                  14059.6
                                            35 dB
                                                    31 WPM
                                                                            2350
                            YW4D
```

Reports Signal to Noise ratio, CW Speed, CQers



What is the Reverse Beacon Network (RBN)?



- Uses any CW or RTTY signal as a beacon
- Multiple Skimmers world-wide record signal strength (S/N ratio in dB) and CW speed (WPM)
- A free "Aggregator" program forwards
 Skimmer spots to a central server
- Central server distributes spots via web page and public telnet servers
- You don't need to have an SDR to use it



How do spots get to you?







Acknowledgements


- RBN web site and first aggregator originated by PY1NB (similar to his other web site, www.dxwatch.com). Felipe pays most of the bills.
- Lots of code by W3OA (aggregator), F5VIH (Spots analysis tool)
- CW Skimmer evangelized and tested by N4ZR (also publishes <u>RBN blog</u>) – "RBN Chief Evangelist"
- Telnet server support by K5TR, W2QO, KM3T





Felipe Ceglia, PY1NB

- Created and maintains the Reverse Beacon Network
- Hosts dxwatch.com and reversebeacon.net





Dick Williams, W3OA

 Created and maintains the current RBN Aggregator software





Nick Sinanis, F5VIH

Wrote the RBN
 Spots Analysis Tool






Pete Smith, N4ZR

- RBN Chief Evangelist
- Skimmertalk Reflector: <u>http://dayton.contesting.com/</u> mailman/listinfo/skimmertalk



What can the RBN do for me?



- It can improve your score
 - Fills spots in band map (SOA, Multi-op)
 - Spots you (very often, if you call CQ properly)
- Entering a contest?
 - Before: Check antenna F/B, signal strength
 - During: See where you are being heard, view skimmer-generated propagation maps
 - After: Compare signal strength with the competition




How can I use RBN to improve my score?

- Make sure the Skimmers find and spot you
- Access RBN via your favorite DX Cluster, for CW and RTTY contests (when allowed)
- RBN will post far more spots than DXers
 - With smaller pileups, less competition
- RBN quickly fills the band map in your logging software
- RBN helps locate clear spots to call CQ (between stations that you may not hear)



How can I use RBN to improve my score (cont'd):



- The RBN reveals band openings, shows where you are being heard
- At K3LR, sunrise on 15m:
 "Spotted by S50ARX-#"
- First EU answered our 15m CQs 25 minutes later




How do I CQ "properly"?



- Send everything at the same consistent speed
 - Never use >/< or +++/--- to change speed in messages
- Call CQ or TEST and send your call twice
 - CQ N6TV N6TV
 - TEST N6TV N6TV
 - CQ N6TV N6TV TEST
- Use proper spacing (let computer send)
 - Don't send with paddles and rush-everything-together
- Change your freq. slightly to get spotted again




What counts as "CQ"?



- Originally just: "CQ", "TEST", and "QRZ"
- VE3NEA Added: "FD", "SS", "NA" and "UP"
- Examples:
 - P5DX P5DX UP
 - SS N6TV N6TV
 - NA N6TV N6TV
 - FD N6TV N6TV FD
- Short calls like "W1F" should always be sent twice to help Skimmer identify it quickly



How to improve your chances in a Skimmer-generated pileup



 Use XIT or the "randomize TX" feature of your logging program to call a bit off frequency.

Bandmaps properties [Alt+H for help]			×	
Spots lifetime (min.) From DX cluster: Op-entered:	30	Spots entered or sent by the Log fields are cleared: Always Never	e operator	
Do not automatically fill the log fields when one grabs a spot ☑ Randomize TX frequency in CW (-100/0/+100 Hz)				




How do I use the RBN to Check My Antennas?



- To test performance, just call CQ on CW or RTTY, check RBN web site (turn beam, repeat)
- Use RBN web site's "Spots Analysis Tool" to compare your signal to the competition
- Download raw data files for deeper analysis
 - Every RBN spot posted since February, 2009 is archived on the RBN web site



Accessing the RBN (SOA, Multi)



- Many DX clusters combine RBN and human spots using AR-Cluster V6 (see www.dxcluster.info for address listing).
 - Some ARC V6 clusters offer CT1BOH spot quality filters (flags busts, uniques)
- dxc.ve7cc.net port 23
 CC Cluster software removes many bad spots (uniques) and dupes



Filtering Spots (old way)



DXSpider

- accept/spots by_zone 1,3,4,6,7,31 and not by WZ7I or call N6TV
- http://www.dxcluster.org/main/filtering en.html#toc1

ARCluster V6

- set dx filter call=N6TV or (unique>1 and (spotterstate=CA or spotterstate=NV or spotterstate=UT))
- http://www.n8noe.us/ARC.html



Filtering Spots (new way)





- Use CC User software by VE7CC to log in to dxc.ve7cc.net port 23
- CC User sets filters with a full-feature, Graphical User Interface (GUI)
- CC Cluster nodes automatically reject "unique" (busted) spots, eliminates dupes
- New AR-Cluster Client by AB5K
- Updated Tutorial:
 - http://reversebeacon.blogspot.com/2013/12/a-new-tutorial-onusing-rbn.html





CC User Filter Dialogs












AR-Cluster Client by AB5K



www.n8noe.us/ARC.html











Many nodes combine RBN and "legacy" (human) spots



- dxc.ve7cc.net port 23 (CC Cluster, many filtering options, use CC User to set them)
- dxc.w9pa.net port 7373 (AR Cluster) set dx extension skimmerquality
- dxc.n7tr.com port 7373 (AR Cluster, but pre-filters to show only spots from Zones 3 and 4)




Real-time propagation maps




- http://www.dxmaps.com
- Click "HF" and band of interest
- Leave page open, it refreshes automatically










Using www.reversebeacon.net





- Great for post-contest analysis
- Plot signal strengths
- Raw data files can be downloaded / analyzed
 - Millions of spots archived





www.reversebeacon.net








www.reversebeacon.net main








Where was I heard?








Plot spots on a map








Which bands are open at my QTH?







Spots analysis tool




REVERS	SE BEACON	NETW	ORK			
welcome main	dx spots skinmers do	wnloads about	contact us			
	download raw data					
Welcome to	spots analisys tool 1 network!					
The Reverse Be	spot search analize and com	pare spots idea. In	stead of beacons actively transmitting signals,			
the RBN is a net how well.	create your filter!					
If you already kn	HF >	e main page.				
So why should y band openings ir	VHF+ >	ou can see				
	HF	I map. You	Check out our blog!			
you, and how str		acons near	Aggregator 2.1 - new insight for Skimmer ops			
Dut the seed has	HF/CW		The newest Aggregator, Version 2.1, is now			







Pick a Date, a Skimmer, add callsigns to compare








And the winner is ... K6XX!







Raw data downloads



REVERS	SE BEA	CON NE	TWC	PK		
welcome main	dx spots skimr	ners downloads	about	contact us		
	download raw da	ata				
Raw data do	spots analisys to	pol				
Data from the RBN	spot search	d analysi	d analysis.			
	create your filte	r! tracts yo	tracts you want. The zipped files can be downloaded by a single click			
on the filename.	HF >					
The data files then amount of data will	VHF+ >	-	viewed by opening in Excel. Note, however, that on busy days the nit. For example, on Saturday, during the 2010 ARRL DX CW contest,			
the RBN produced full daily data set, o	e Microsoft Access or other data tools to examine and manipula					
The only thing that			that you share your ideas for analyzing them, as well as any results, it on our RBN blog. Of course, you will retain full rights for any other			
with the RBN comr		it on our				
publication. Please		keep in	touch with	us.		
Click on the year, a	HF/SSB	ee availa	ee available data. You can also use the controls below.			
collapse all month	VHF+/CW					
2012	VHF+/SSB					
January	1.8/3.5/7MHz					
February 01 Wedne	14/21/28MHz	20	20120201.zip			
	10/18/24MHz		120201.zij			
03 Friday	1089	KBytes 20	120203.zij			

Raw data is text file, Comma Separated Values



```
callsign,de_pfx,de_cont,freq,band,dx,dx_pfx,dx_cont,mode,db,date,speed,tx_mode
    JE1SGH,JA,AS,28032.6,10m,K6UW,K,NA,CQ,29,2014-02-15 00:00:00,32,CW
    XV4Y,3W,AS,14041.1,20m,PT5T,PY,SA,CQ,22,2014-02-15 00:00:00,28,CW
    XV4Y,3W,AS,14021,20m,PX2F,PY,SA,CQ,23,2014-02-15 00:00:00,23,CW
    NC7J,K,NA,28005.5,10m,N2IC,K,NA,CQ,11,2014-02-15 00:00:00,33,CW
```

Total World-Wide RBN CW spots, CQ WW:

2013: 5,743,545 (33.2 spots per *second*)

2014: 6,200,340 (35.9) – up 8.0%

2015: 7,085,553 (41.0) – up 14.0%

2016: 6,060,130 (35.1) – down 14.5%

ARRL DX CW:

2014: 4,146,399 (86,383 spots per *hour*)

2015: 5,537,017 (115,354) – up 33.5%

2016: 3,924,585 (81,762) – down 29.1%

2017: 4,285,719 (89,286) - up 9.2%





What's the Average CW Speed of a Spot?



CQ WW CW:

2013: 30.6 WPM

2014: 30.8

2015: 30.7

2016: 30.8

ARRL DX CW:

2014: 29.6 WPM

2015: 30.1


2016: 29.9

2017: 29.6





RTTY Skimmer Stats



CQ World-Wide RTTY (48 hours):

2015: 922,311 (5.3 spots per *second*)

2016: 994,212 (5.8) - up 7.8%

 ARRL January RTTY Roundup (30) hours):

2016: 457,033 (15,234 spots per *hour*) 2017: 470,377 (15,679) – up 2.9%




How can I help?



- Set up an SDR, feed Skimmer Spots to the RBN, using the Aggregator program
 - More skimmers needed in Asia/Africa/South America
- Call a bit off frequency (Win-test and N1MM both provide automatic randomization if desired)



What's New?



- NCDXF and other HF Beacons can be spotted on RBN
 - reversebeacon.blogspot.com/2014/02/ncdxfbeacon-spotting-redux.html
- RTTY Skimmer Server 1.2
- CW Skimmer 1.91
- Aggregator v4.3
- Skimmer Server testing by JF2IWL using Red Pitaya and S9-C SDRs



For more information




- http://www.reversebeacon.net
- http://www.dxmaps.com
- http://www.bcdxc.org/ve7cc/default.htm#download
- http://www.dxatlas.com/CwSkimmer
- http://www.dxatlas.com/SkimServer
- http://www.srl-llc.com/ (QS1R SDR)
- http://www.ba4tb.qth.com/ (S9-c SDR)
- http://microtelecom.it/perseus/ (Perseus SDR)
- https://redpitaya.com/ (Red Pitaya)





For more information



- http://www.dxengineering.com/parts/ins-rf-pro-<u>1b</u> (RF Pro-1B loop antenna)
- http://www.dxengineering.com/parts/dxe-arah3-1p (Active Broadband Dipole antenna)
- http://www.pvrc.org/~n4zr/rbn.pdf
- http://reversebeacon.blogspot.com/2013/12/anew-tutorial-on-using-rbn.html
- http://reversebeacon.blogspot.com
- http://www.ve7cc.net/
- http://www.qrz.com/db/n6tv



Questions?



